


# ideal lux | Nova




## DOWNLIGHT



Code	248196
Item name	NOVA 30W 3000K BK
Source	LED COB PHILIPS
Power	30W
Driver included	ON-OFF
Driver available	1-10V   DALI
Lumen	3150 Lm
MacAdam	-
Beam	38° <b>elimina riga vuota</b>
CCT	3000K
CRI	≥90
UGR	<22
LED Life	30.000 h
Insulation class	Class II
IP	20
Material	Aluminum
Warranty	5 years
Net Weight	1,160 Kg
Volume	0,0039 m <sup>3</sup>
Base / Hole	ø 14 cm



ø 15cm



13,8

### IDEAL LUX s.r.l.

Via Taglio Destro, 32, 30035 Mirano (Venezia)  
Tel. +39 041 5790500, Fax +39 041 8872349, E-mail info@ideal-lux.com  
www.ideal-lux.com



**Code** 248370  
**Item name** NOVA DRIVER 1-10V 30W  
**Power** 30W  
**Output** 750 mA  
**Range** 300-900 mA  
**Measure** 167 x 41 x 32 mm



**Code** 248592  
**Item name** NOVA DRIVER DALI 36W  
**Power** 36W  
**Output** 700 mA  
**Range** 200-1200 mA  
**Measure** 167 x 39 x 30 mm



**Code** 248608  
**Item name** NOVA LENTE 15° PER 30W